

CONCIERTO 500

Portable Compact Personal Array System



CONCIERTO 500

Especificaciones Técnicas

Amplifier	
Inputs	XLR/TRS combo jack stereo RCA & 1/8" AUX input
Outputs	XLR balanced line output
Power output	RMS 500W / PEAK 1000W
Volume	volume control each channel, 2-band EQ
Power input	100-240V ~50/60 Hz switchable
Features	Class D amplifier and switching power design Power/clip indicator Excellent compressor
Subwoofer	active vented subwoofer
Frequency response	55-200 Hz
Max output spl	114dB (at max amp output)
Driver	8" subwoofer, 1.5" vc 33oZ (CONCIERTO 500SW8)
Cabinet	PP plastic
Grill	1.0mm steel
Satellite	passive full-range speaker
Frequency response	180-20K Hz
Max output spl	114dB
Impedance	4 ohms
Driver	6*2.75" full range line array
Cabinet	PP plastic
Grill	1.0mm steel
MEAS / G.W.	10.5*20*85.5CM/1PC/5KG(SAT) 52*41.5*52.5CM/1PC/14.5KG (SUB)



@showco_shop_

showco.com.mx
info@showco.com.mx

CDMX 📞 (55) 1857 6703 (55) 5709 9903

MONTERREY 📞 (81) 8374 2159 (81) 8375 4536 📞 81 1909 4421

GUADALAJARA 📞 (33) 31097984

CANCÚN 📞 (55) 7571 9985